

Investigation of Novel Method of Spherical Aberration Correction for Enhanced Spherical Hybrid Reflector Antennas

Oleg P. Ponomarev

Baltic Fishing Fleet State Academy
236035, Russia, Kaliningrad, Molodezhnaya, 6

1. Introduction

Science achievements in methods of processing of the radar-tracking information define directions of development of antenna systems. These are expansion of aims and functions of antennas, achievement of optimal electric characteristics with regard to mass, dimensional and technological limits. Hybrid reflector antennas (HRA's) have the important part of the radars and modern communication systems. In HRA the high directivity is provided by system of reflectors and form of the pattern of the feed, and scanning possibility is provided by feeding antenna array. Artificial network, generic synthesis and evolution strategy algorithms of the phased antenna arrays and HRA's, numerical methods of the analysis and synthesis of HRA's on the basis of any finite-domain methods of the theory of diffraction, the wavelet analysis and other methods, have been developed for the last decades. The theory and practice of antenna systems have in impact on the ways of development of radars: radio optical systems, digital antenna arrays, synthesised aperture radars (SAR), the solid-state active phased antenna arrays (Fourikis, 1996).

However these HRA's has a disadvantage – impossibility of scanning by a beam in a wide angle range without decrease of gain and are worse than HRA's on the basis of reflector with a circular profile. In this antennas need to calibrate a phase and amplitude of a phased array feeds to yield a maximum directivity into diapason of beam scanning (Haupt, 2008).

Extremely achievable electric characteristics HRA are reached by optimization of a profile of a reflector and amplitude-phase distribution of feeding antenna array (Bucci et al., 1996). Parabolic reflectors with one focus have a simple design, but their worse then multifocuses reflectors. For example, the spherical or circular cylindrical forms are capable of electromechanical scanning the main beam. However the reflectors with a circular profile have a spherical aberration that limits their application.

The aim of this article is to elaborate the combined mathematical method of the diffraction theory for the analysis of spherical HRA's of any electric radius and to demonstrate a novel method of spherical aberration correction. The developed mathematical method is based on a combination of eigenfunctions/geometrical theory diffraction (GTD) method.

2. Methods of Analysis and Synthesis of Hybrid Reflector Antennas

The majority of HRA's use the parabolic and elliptic reflectors working in the range of submillimeter to decimeter ranges of wave's lengths. A designs of multibeam space basing

HRA's have been developed by company Alcatel Alenia Space Italy (AAS-I) for SAR (Llombart et al., 2008). The first HRA for SAR was constructed in a Ku-range in 1997 for space born Cassini. These HRA are equipped with feeds presented as single multimode horns or based on clusters and have two orthogonal polarizations. The parabolic reflector of satellite HRA presented in (Young-Bae & Seong-Ook, 2008) is fed by horn antenna array and has a gain 37 dB in range of frequencies 30,085-30,885 GHz. A tri-band mobile HRA with operates by utilizing the geo-stationary satellite Koreasat-3 in tri-band (Ka, K, and Ku) was designed, and a pilot antenna was fabricated and tested (Eom et al., 2007).

One of the ways of development of methods of detection of sources of a signal at an interference with hindrances is the use of adaptive HRA. The effective algorithm of an estimation of a direction of arrival of signals has been developed for estimation of spectral density of a signal (Jefferies & Warnick, 2008). The adaptive beamformer is used together with HRA and consist of a parabolic reflector and a multichannel feed as a planar antenna array. A mathematical method on the basis of the GTD and physical optics (PO), a design multibeam multifrequency HRA centimeter and millimeter ranges for a satellite communication, are presented in (Jung et al., 2008). In these antennas the basic reflector have a parabolic and elliptic forms that illuminated by compound feeds are used. Use of metamaterials as a part of the feed HRA of a range of 30 GHz is discussed in (Chantalat et al., 2008). The wide range of beam scanning is provided by parabolic cylindrical reflectors (Janpugdee et al., 2005), but only in once plane of the cylinder. A novel hybrid combination of an analytical asymptotic method with a numerical PO procedure was developed to efficiently and accurately predict the far-fields of extremely long, scanning, very high gain, offset cylindrical HRA's, with large linear phased array feeds, for spaceborn application (Tap & Pathak, 2006).

Application in HRA the reflectors with a circular profile is limited due to spherical aberration and lack of methods of it correction (Love, 1962). The field analysis in spherical reflectors was carried out by a methods PO, geometrical optics (GO), GTD (Tingye, 1959), integrated equations (Elsherbeni, 1989). The field analysis was carried out within a central region of reflector in the vicinity focus $F = a/2$ (a - reflector radius), where beams are undergone unitary reflections. Because of it the central region of hemispherical reflectors was fed and their gain remained low.

However it is known that diffraction on concave bodies gives a number of effects which have not been found for improvement of electric characteristics of spherical antennas. Such effects are multireflections and effect of "whispering gallery" which can be seen when the source of a field is located near a concave wall of a reflector. By means of surface waves additional excitation of peripheral areas of hemispherical reflector can raises the gain and decreases a side lobes level (SLL) of pattern (Ponomarev, 2008).

Use of surface electromagnetic waves (EMW) together with traditional methods of correction of a spherical aberration are expedient for electronic and mechanical control of pattern in the spherical antennas.

The existing mathematical methods based on asymptotic techniques GTD, GO and PO does not produce correct solutions near asymptotic and focal regions. Numerical methods are suitable for electrically small hemisphere. Another alternative for the analysis of HRA's is combine method eigenfunctions/GTD technique. This method allows to prove use of surface EMW for improvement of electric characteristics spherical and cylindrical HRA's and to give clear physical interpretation the phenomena's of waves diffraction.

3. Spherical Hybrid Reflector Antennas

3.1 The Main Characteristics of Surfaces Electromagnetic Waves

For the first time surface wave properties were investigated by Rayleigh and were named "whispering gallery" waves, which propagate on the concave surface of circumferential gallery (Rayleigh, 1945). It was determined that these waves propagate in thin layer with equal wave length. This layer covers concave surface. On the spherical surface the energy of Rayleigh waves is maximal and change on the spherical surface by value $J_m(kr)/\sqrt{r}(P_n(\cos\theta) + A \cdot Q_n(\cos\theta))$, where $J_m(kr)$ is cylindrical Bessel function of the 1-st kind, $P_n(\cdot), Q_n(\cdot)$ are Legendre polynomials, A is the constant coefficient, $k = 2\pi/\lambda$ is the number of waves of free space, (r, θ) are spherical coordinates. The same waves propagate on the solid surface of circumferential cylinder and the acoustic field potential for longitudinal and transverse waves is proportional to the values $J_\nu(k\rho)e^{i\nu\varphi}, J'_\nu(k\rho)e^{i\nu\varphi}$, where $J'_\nu(k\rho)$ is derivative of Bessel function about argument, $\nu \approx a$ is constant propagate of surface acoustic wave on cylinder with radius of curvature a , (ρ, φ) are cylindrical coordinates (Grase & Goodman, 1966). In electromagnetic region the surface phenomena at the bent reflectors with perfect electric conducting of the wall, were investigated (Miller & Talanov, 1956). It was showed that their energy is concentrated at the layer with approximate width $a - (\nu - \nu^{1/3})/k$. The same conclusion was made after viewing the diffraction of waves on the bent metallic list that illuminated by waveguide source and in bent waveguides (Shevchenko, 1971).

A lot of letters were aimed at investigating the properties of surface electromagnetic waves (EMW) on the reserved and unreserved isotropic and anisotropic boundaries. The generality of approaches can be clearly seen. To make mathematic model an impressed point current source as Green function. For example, for spiral-conducting parabolic reflector the feed source is a ring current, for elliptic and circumferential cylinder the feed source is an impressed thread current, for spherical perfect electric conducting surface the feed source is a twice magnetic sheet. So far surface phenomena of antenna engineering were considered to solve the problem of decreasing the SLL of pattern.

3.2 Methods of Correction of Spherical Aberration

A process of scanning pattern and making a multibeam pattern without moving the main reflector explains the advantage of spherical antennas. On the one hand the spherical aberration makes it difficult to get a tolerable phase errors on the aperture of the hemispherical dish. On the other hand the spherical aberration allows to extend functionalities of the spherical reflector antennas (Spencer et al., 1949). As a rule the diffraction field inside spherical reflector is analyzed by means of uniform GTD based for large electrical radius of curvature ka of reflector. An interferential structure of the field along longitudinal coordinate of the hemispherical reflector z has a powerful maximum near a paraxial focus $F = ka/2$ (fig.1) (Schell, 1963). The change of parameter z from 0 to 1 is equal to the change of radial coordinate r from 0 to a . As an angle value of the reflector has been reduced one can see the contribution of the diffraction field from the edges of the reflector.

According to the field distribution shown at fig.1 a feed of the spherical reflector can consist of set of discrete sources disposed from paraxial focus $z=0,5$ to apex of the reflector $z=1$. The separate discrete source illuminates a part of ring on the aperture limited by the beams unitary reflected from concave surface of the reflector.




Fig.1. Distribution of the electrical field component $|E_x|$ along axes of the spherical reflector at the wave length $\lambda = 3,14 \text{ cm}$: thick line corresponds to curvature radius of the reflector $a = 100 \text{ cm}$; thin line - $a = 50 \text{ cm}$; points - $a = 25 \text{ cm}$

The results of the investigation of hemispherical reflector antenna with radius of curvature $2a = 3 \text{ m}$ at frequency $11,2 \text{ GHz}$, are discussed (Tingye, 1959). At the excitation of the central path of the reflector with diameter $1,1 \text{ m}$ phase errors at the aperture were less than $\pi/8$, SLL of the pattern were less -25 dB .

Using the channel waveguides as a corrected line source of the spherical antennas seems to be an effective way to reduce the phase errors at the aperture of a spherical reflector (Love, 1962). This line corrected source guarantees the required distribution of the field with illuminated edges of the reflector at the sector of 70° and guarantees electromechanical scattering of the pattern over sector of 110° . An array of waveguide slot sources with dielectric elements for correcting the amplitude-phase field distribution along aperture can be used as the line feed source (Spencer et al., 1949).

Integral equations method is the effective way to solve the problem of spherical aberration correction for reflector with any electrical radius (Elsherbeni, 1989), but at the same time it has difficult physical interpretation of the results and the accuracy is not guaranteed. In theory and practice of correction of spherical aberration is considered within the limits of central area aperture where rays are unitary reflected from concave surface. The edges areas of aperture are not considered for illumination. However, when an incident wave falls on hemispherical reflector, surface EMW propagate along its concave surface. The amplitude of surface waves is concentrated in thin layer with width $\Delta r \approx \lambda$ that is bordered with the reflecting surface. Using the amplitude stability of surface EMW with respect to surface curvature is very important for spherical aberration correction for reflectors with $2\theta = 180^\circ$.

3.3 Solve of Helmholtz Equation in Spherical Coordinates and Diffraction Problems

It is known that diffraction on concave bodies gives a series of effects, which are still not practically used for improving electrical characteristics of spherical reflector antennas. These are the effects of multiple reflections and the effect of "whispering gallery", that show themselves when the source of electromagnetic field is disposed near the reflector.

Solve of Helmholtz equation about component of electrical field in the spherical coordinates (r, θ, φ) with using a group of rotates $E_+ = -1/\sqrt{2}(E_\varphi + iE_\theta)$, $E_0 = E_r$, $E_- = 1/\sqrt{2}(E_\varphi - iE_\theta)$ will look as series of cylindrical $f_l^*(r)$ and spherical functions $T_{m,n}^l(\frac{\pi}{2} - \varphi, \theta, 0)$ (Gradshteyn & Ryzhik, 2000)

$$\left. \begin{aligned} E_0(r, \theta, \varphi) &= \sum_{l=0}^{\infty} f_l^0(r) \sum_{n=-l}^l \alpha_{l,n} T_{0n}^l(\frac{\pi}{2} - \varphi, \theta, 0) \\ E_+(r, \theta, \varphi) &= \sum_{l=0}^{\infty} f_l^+(r) \sum_{n=-l}^l \beta_{l,n} T_{1n}^l(\frac{\pi}{2} - \varphi, \theta, 0) \\ E_-(r, \theta, \varphi) &= \sum_{l=0}^{\infty} f_l^-(r) \sum_{n=-l}^l \gamma_{l,n} T_{-1n}^l(\frac{\pi}{2} - \varphi, \theta, 0) \end{aligned} \right\}$$

where $\alpha_{l,n}, \beta_{l,n}, \gamma_{l,n}$ - weighting coefficients.

Taking into consideration the generalized spherical functions over joined associated Legendre functions $P_l^1(\cos\theta)$ and polynomial Jacobi $P_{l-1}^{(0,2)}(\cos\theta)$, common solving of wave equation about components of electrical field can be written as follows

$$\left. \begin{aligned} E_r &= \sum_{l=1}^{\infty} A_l \frac{J_{l+1/2}(kr)}{(kr)^{3/2}} P_l^1(\cos\theta) e^{-i(\pi/2-\varphi)}; \\ E_\theta &= \frac{i(1+\cos\theta)}{2} \sum_{l=1}^{\infty} \frac{C_1 \cos^2 \frac{\pi l}{2}}{\sqrt{l(l+1)}} \left[\frac{J_{l+3/2}(kr)}{(kr)^{1/2}} - (l+1) \frac{J_{l+1/2}(kr)}{(kr)^{3/2}} \right] P_{l-1}^{0,2}(\cos\theta) e^{-i(\pi/2-\varphi)} + \\ &\quad + i \frac{1+\cos\theta}{2} \sum_{l=1}^{\infty} C_2 \sin^2 \frac{\pi l}{2} \frac{J_{l+1/2}(kr)}{(kr)^{1/2}} P_{l-1}^{0,2}(\cos\theta) e^{-i(\pi/2-\varphi)}; \\ E_\varphi &= -\frac{1+\cos\theta}{2} \sum_{l=1}^{\infty} C_1 \frac{\sin^2 \frac{\pi l}{2}}{\sqrt{l(l+1)}} \left[\frac{J_{l+3/2}(kr)}{(kr)^{1/2}} - (l+1) \frac{J_{l+1/2}(kr)}{(kr)^{3/2}} \right] P_{l-1}^{0,2}(\cos\theta) e^{-i(\pi/2-\varphi)} - \\ &\quad - \frac{1+\cos\theta}{2} \sum_{l=1}^{\infty} C_2 \cos^2 \frac{\pi l}{2} \frac{J_{l+1/2}(kr)}{(kr)^{1/2}} P_{l-1}^{0,2}(\cos\theta) e^{-i(\pi/2-\varphi)}. \end{aligned} \right\} \quad (1)$$

where A_l, C_1, C_2 are the constant coefficients.

The analysis of the equations (1) shows that eigenwaves propagate into hemisphere with angles $\pm\theta$. Each wave propagates with its constant of propagation $\gamma_{m(n)}$ along virtual curves with radiuses $r_{m(n)} = \gamma_{m(n)}/k$ with maintaining vectors of polarization about component E_r ,

and E_φ (fig.2). In the area near points $r_{m(n)} = \gamma_{m(n)}/k$ the aperture of reflector is coordinated with surrounding space under conditions of eigenwaves propagation.




Fig.2. Waves propagation in to hemispherical reflector

The amplitude of the electrical field strength vector \vec{E} with arbitrary angle φ is defined as

$$|\vec{E}| = \sqrt{E_r^2 + E_\varphi^2},$$

where $E_r = \sqrt{(\text{Re } E_r)^2 + (\text{Im } E_r)^2}$; $E_\varphi = \sqrt{(\text{Re } E_\varphi)^2 + (\text{Im } E_\varphi)^2}$;

$$\text{Re } E_r = (kr)^{-3/2} \sum_m A_{\gamma_m} J_{\gamma_m}(kr) \cos(\gamma_m(\theta - \pi/2)) \cdot \cos \varphi;$$

$$\text{Im } E_r = (kr)^{-3/2} \sum_m A_{\gamma_m} J_{\gamma_m}(kr) \sin(\gamma_m(\theta - \pi/2)) \cdot \cos \varphi;$$

$$\text{Re } E_\varphi = \sum_n A_{\gamma_n} \left[\frac{J_{\gamma_n+1}(kr)}{(kr)^{1/2}} - (\gamma_n + 1/2) \frac{J_{\gamma_n}(kr)}{(kr)^{3/2}} \right] \times \cos(\gamma_n(\theta - \pi/2)) \cdot \sin \varphi;$$

$$\text{Im } E_\varphi = \sum_n A_{\gamma_n} \left[\frac{J_{\gamma_n+1}(kr)}{(kr)^{1/2}} - (\gamma_n + 1/2) \frac{J_{\gamma_n}(kr)}{(kr)^{3/2}} \right] \times \sin(\gamma_n(\theta - \pi/2)) \cdot \sin \varphi;$$

$$A_{\gamma_n} = \frac{1}{N_{\gamma_n}} \left[\left(1 - \frac{1}{2\gamma_n} \right) \int_0^{ka} F(z) J_{\gamma_n+1}(z) \frac{dz}{\sqrt{z}} + \left(1 + \frac{1}{2\gamma_n} \right) \int_0^{ka} F(z) J_{\gamma_n-1}(z) \frac{dz}{\sqrt{z}} \right]; A_{\gamma_n} = \frac{1}{N_{\gamma_n}} \int_0^{ka} F(z) z^{1/2} J_{\gamma_n}(z) dz;$$

$$N_{\gamma_n} = \int_0^{ka} [J_{\gamma_n}(z)]^2 dz; N_{\gamma_n} = \left(1 - \frac{1}{2\gamma_n} \right)^2 \int_0^{ka} [J_{\gamma_n+1}(z)]^2 \frac{dz}{z} - \left(1 + \frac{1}{2\gamma_n} \right)^2 \int_0^{ka} [J_{\gamma_n-1}(z)]^2 \frac{dz}{z}; F(z) \text{ is the given}$$

distribution of the field on the aperture of a hemispherical reflector.

The distribution of electric field on the surface of virtual polarized cone inside hemispherical reflector with electrical radius of curvature $ka=40$ and uniform distribution of incident field on the aperture $F(z)=F(kr)=1$ has two powerful interferential maximums. First maximum is placed near paraxial focus from $kr=10$ to $kr=30$, second maximum is placed

near reflected surface $kr=ka$ (fig.3). It is possible to observe the redistribution of interferential maximums along radial axes on a virtual cone by increasing the angle value of the cone.




Fig.3. Distribution of the electric field on the surface of virtual polarization cone with angle value $\Theta=2^\circ$ (a) and $\Theta=10^\circ$ (b)

Obviously the feed of hemispherical reflector presented as set of discrete sources that must be placed at the polarized cone according to a structure of power lines and amplitude-phase distribution of the field. According to distribution of electromagnetic field along radial axes on the arbitrary section (fig.3), the line phased feed can consist of discrete elements. It is obvious that this phased feed have an advantage about absence a shadow region of aperture. According to increase cone value Θ of polarized cone is decrease an efficiency of excitation the aperture.

Focusing properties of the edge areas of the hemispherical reflector are displayed when solving the problem of excitation a perfect electric conducting hemispherical surface by the symmetrical ring of electric current with coordinates (kr', θ') , where $kr' \sin \theta' \gg 1$. The ring of electric current is equivalent to double magnetic sheet with thickness d and density of electrostatic charge $\pm\sigma$ for neighboring sheets (fig.4).

Let us define scalar Green function $\Gamma = \Gamma(kr, \theta, kr', \theta')$ as a function satisfactory to homogeneous Helmholtz equation anywhere, except the ring current, where electrostatic potential $\eta = \sigma \cdot d$ exposes a jump: $\partial\Gamma/\partial\theta|_{\theta=\theta'+0} - \partial\Gamma/\partial\theta|_{\theta=\theta'-0} = -4\pi\eta = -4\pi\sigma d = -4\pi\sigma d \delta(kr - kr')$. Let us search Green function satisfactory to radiation condition $\lim_{r \rightarrow \infty} \left(r \frac{\partial\Gamma}{\partial r} - ikr\Gamma \right) = 0$ and boundary condition $\partial/\partial z (z^{3/2} \Gamma)_{z=ka} = 0$ as

$$\Gamma = \frac{-8\pi}{ka} \left(\frac{kr'}{kr} \right)^{3/2} \sin \theta' \times \sum_m \frac{\gamma_m}{v_m(v_m+1)} \frac{J_{\gamma_m}(kr) J_{\gamma_m}(kr')}{J_{\gamma_m}(ka) \frac{\partial^2 J_{\gamma_m}(ka)}{\partial \gamma \partial (kr)}} \times \begin{cases} L_{v_m}(\cos \theta) P_{v_m}^1(\cos \theta'), \theta > \theta' \\ L_{v_m}(\cos \theta') P_{v_m}^1(\cos \theta), \theta < \theta' \end{cases} \quad (2)$$

where $L_{v_m}(\cos \theta) = Q_{v_m}^1(\cos \theta) + i \frac{\pi}{2} P_{v_m}^1(\cos \theta)$; $v_m = \gamma_m - 1/2$; $Q_{v_m}^1(\cos \theta)$ - associated Legendre functions of 2-nd kind.




Fig.4. Geometry of excitation of hemispherical reflector by electric current ring

Consider one-connected area D on complex surface γ and distinguish points $\gamma_1, \gamma_2, \dots, \gamma_m$ for this surface as solutions of Neumann boundary condition for Green function. In every point of the area D function Γ is univalent analytic function, except points $\gamma_1, \gamma_2, \dots, \gamma_m$ where it has simple poles. Let us place the field source on the concave hemisphere surface ($kr' = ka$). Using Cauchy expression present (2) as a sum of waves and integral with contour that encloses part of the poles γ , satisfactory to the condition $ka < \gamma < ka - ka^{1/3}$ and describing the geometrical optic rays field. In the distance from axis of symmetry ($\gamma_m \theta \gg 1$), the contour integral is given as

$$\frac{-2\sqrt{ka}}{(kr)^{3/2}} \sqrt{\frac{\sin \theta'}{\sin \theta}} \int_{c_1} \frac{J_{\nu+1/2}(kr)}{J'_{\nu+1/2}(ka)} \{e^{i[(\nu+1/2)(\theta+\theta')+\pi/2]} + e^{2i[(\nu+1/2)(\theta-\theta')]} \} d\nu.$$

The sign "+" at index exponent corresponds for $\theta > \theta'$ and the sign "-" for $\theta < \theta'$. A factor $(\sin \theta' / \sin \theta)^{1/2}$ explains geometrical value of increasing of rays by double concave of the hemispherical reflector with comparison to cylindrical surface. First component in contour integral correspond a brighten point at the distance part of the ring with electrical current, second component – brighten point at the near part of the ring. Additional phase $\pi/2$ is interlinked with passing of rays through the axis caustic.

In the focal point area ($\gamma_m \theta \leq 1$) the contour integral can be written as

$$\frac{-4(\pi/2)^{1/2}(ka)^{1/2}}{(kr)^{3/2}} \sqrt{\frac{\theta \sin \theta'}{\sin \theta}} \int_{c_1} \frac{(\nu+1/2)^2}{\sqrt{\nu(\nu+1)}} J_1((\nu+1/2)\theta) \frac{J_{\nu+1/2}(kr)}{J'_{\nu+1/2}(ka)} e^{i[(\nu+1/2)\theta'+\pi/4]} d\nu.$$

In accordance with a stationary phase method the amplitude and phase structure of the field in tubes of the rays near a caustic can be investigated.

The distribution of the radial component of the electrical field E_r along axis of the hemisphere with radius of curvature $a = 22,5 \text{ cm}$ for uniform distribution field on the

aperture $\theta = \pi/2$ has two powerful interferential maximums at the wave length $\lambda = 6,28\text{cm}$ (dotted line), $\lambda = 2,513\text{cm}$ (thin line) and $\lambda = 0,838\text{cm}$ (thick line) (fig.5).

First maximum is near paraxial focus $F = ka/2$ and is caused by diffraction of the rays, reflected from concave surface at the central area of the reflector. Second interferential maximum characterizes diffraction properties of the edges of hemispherical reflector. In this area the rays test multiple reflections from concave surface and influenced by the "whispering gallery" waves.

At decrease the wavelength λ first diffraction maximum is displaced near a paraxial focus $F = 10\text{cm}$, a field at the area $r < f$ is decreasing quickly as well as the wavelength. Second diffraction maximum is narrow at decrease of the wavelength, one can see redistribution of the interferential maximums near paraxial focus.




Fig.5. Diffraction properties of the hemisphere dish with radius of curvature $a = 22,5\text{cm}$

In accordance with the distribution of the field, a spherical antenna can have a feed that consists of two elements: central feed in the area near paraxial focus and additional feed near concave surface hemisphere. This additional feed illuminates the edge areas of aperture by surface EMW. The use of additional feed can increase the gain of the spherical antennas.

3.4 Experimental Investigation of Pattern of Spherical Hybrid Antenna

Accordingly a fig.5, the feed of the spherical HRA can consist of two sections. First section is ordinary feed as line source arrays that place near paraxial focus. Second section is additional feed near concave spherical surface and consists of four microstrip or waveguide sources of the surface EMW. An aperture of the additional feed must be placed as near as possible to longitudinal axis of the reflector. The direction of excitation of the additional sources is twice-opposite in two perpendicular planes. This compound feed of the spherical reflector can control the amplitude and phase distribution at the aperture of the spherical antenna.

Extended method of spherical aberration correction shows that additional sources of surface EMW must be presented as the aperture of rectangular waveguides or as microstrip sources with illumination directions along the reflector at the opposite directions. By phasing of the

additional and main sources and by choosing their amplitude distribution one can control SLL of the pattern and increase the gain of the spherical antenna. Experimental investigations of the spherical reflector antenna with diameter $2a = 31\text{cm}$ at wave length $\lambda = 3\text{cm}$ show the possibility to reduce the SLL and increase the gain by 10–12% by means of a system control of amplitude-phase distribution between the sources (fig.6a). For correction spherical aberration at full aperture the main feed 2 (for example horn or line phase source) used for correction spherical aberration in central region of reflector 1 and placed at region near paraxial focus $F = a/2$. Additional feed 3 consist of two (four) sources that place near reflector and radiated surface EMW in opposite directions. Therefore additional feed excite ring region at the aperture. By means of mutual control of amplitude-phase distribution between feeds by phase shifters 4, 5, 9, attenuators 6, 7, 10 and power dividers 8, 11 (waveguide tees), can be reduce SLL. There are experimental data of measurement pattern at far-field with SLL no more -36 dB (fig.7) (Ponomarev, 2008).




Fig.6. Layout of spherical HRA with low SLL (a) and monopulse feed of spherical HRA (b)

For allocation of the angular information about position of the objects in two mutually perpendicular planes the monopulse feed with the basic source 2 and additional sources 3 in two mutually perpendicular areas is under construction (fig. 6b). Error signals of elevation Δ_ϵ and azimuth Δ_β and a sum signal Σ are allocated on the sum-difference devices (for example E- H-waveguide T-hybrid).




Fig.7. Pattern of spherical HRA excited with main feed (1); excited the main and additional feeds (2): a – main lobe; b – 1-st side lobe

4. Conclusion

The review of methods of the analysis, synthesis and design features of HRA is carried out. The ways of improvement of their electrical characteristics at the expense of usage of reflectors with the circular profile and the linear phased feeds with additional sources of surface EMW or leakage waves of waveguide type is defined. Disadvantages of methods of correction of a spherical aberration on the basis of usage of a subreflector of the special form and the linear phased irradiator are revealed. The new method of correction of a spherical aberration by illuminating of edge areas of aperture of hemispherical reflector surface EMW

is developed. Solves of the Maxwell equations with usage of techniques of the spherical rotates, diffractions of EMW precisely describing and explaining a physical picture on a hemispherical surface are received. The solution of a problem of diffraction of plane EMW on a hemispherical reflector has allowed to define borders and the form interference maximums in internal area of reflectors with any electric radius. By the solve of a problem of excitation of aperture of hemispherical reflector by current ring the additional requirements to form of the pattern of sources of surface EMW are developed. Expressions for Green's function as sum of waves and beam fields according to approaches of GTD are found. The behavior of a field in special zones is found out: near caustics and focal points. The method of control of amplitude and phase fields distribution on the aperture of spherical HRA is developed. At the expense of phasing of the basic and additional feeds and control of amplitudes and phases between them it was possible to reduce the SLL no more - 36 dB and to increase the gain by 10-12 %. The spherical HRA allows: to control amplitude end phase fields distribution on all aperture of HRA; to provide high efficiency because of active radiating units of feeds do not shade of aperture; to realize a combined amplitude/multibase phase method of direction finding, polarization selection of signals. The HRA's provide: increasing of range of radars operation by 8-10 %; reduce the error of measurement of coordinates at 6-8 times; reduction of probability of suppression of radar by active interferences by 20-30 %.

On the basis of such antennas use of MMIC technology of fabricate integrated feeds millimeter and centimeter waves is perspective. Embedding the micromodules into integral feeding-source antennas for HRA's for processing of the microwave information can be utilized for long-term evolution multifunctional radars. Future work includes a more detailed investigation the antennas for solving a problem of miniaturization of feeds for these antennas by means of MMIC technologies.

5. References

- Bucci, O.M., Elia, G.D. & Romito, G. (1996). Synthesis Technique for Scanning and/or Reconfigurable Beam Reflector Antennas With Phase-only Control. *IEE Proc.-Microw. Antennas Propag.*, Vol. 143, No. 5, October, p.p. 402-412.
- Chantalat, R., Menudier, C., Thevenot, M., Monediere, T., Arnaud, E. & Dumon, P. (2008). Enhanced EBG Resonator Antenna as Feed of a Reflector Antenna in the Ka Band. *IEEE Antennas and Wireless Propag.*, Vol. 7, p.p. 349-353.
- Elsherbeni, A. (1989). High Gain Cylindrical Reflector Antennas with Low Sidelobes. *AEU*, Band 43, Heft 6, p.p. 362-369.
- Eom, S.Y., Son, S.H., Jung, Y.B., Jeon, S.I., ganin, S.A., Shubov, A.G., Tobolev, A.K. & Shishlov, A.V. (2007). Design and Test of a Mobile Antenna System With Tri-Band Operation for Broadband Satellite Communications And DBS Reception. *IEEE Trans. on Antennas and Propag.*, Vol. 55, No. 11, November, p.p. 3123-3133.
- Fourikis, N. (1996). *Phased Array-Based Systems and Applications*, John Willey & Sons., Inc.
- Gradshteyn, I.S. & Ryzhik, I.M. (2000). *Table of Integrals, Series and Products*, 930, 8.533, Academic Press, New York.
- Grase, O. & Goodman, R. (1966). Circumferential waves on solid cylinders. *J. Acoust. Soc. America*, Vol. 39, No. 1, p.p.173-174.

- Haupt, R.L. (2008). Calibration of Cylindrical Reflector Antennas With Linear Phased Array Feeds. *IEEE Trans. on Antennas and Propag.*, Vol. 56, No. 2, February, p.p. 593-596.
- Janpugdee, P., Pathak, P. & Burkholder, R. (2005). A new traveling wave expansion for the UTD analysis of the collective radiation from large finite planar arrays. *IEEE AP-S/URSI Int. Symp.*, Washington, DC, July.
- Jeffs, B. & Warnick, K. (2008). Bias Corrected PSD Estimation for an Adaptive Array with Moving Interference. *IEEE Trans. on Antennas and Propag.*, Vol. 56, No. 7, July, p.p. 3108-3121.
- Jung, Y.B. & Park, S.O. (2008). Ka-Band Shaped Reflector Hybrid Antenna Illuminated by Microstrip-Fed Horn Array. *IEEE Trans. on Antennas and Propag.*, Vol. 56, No. 12, December, p.p. 3863-3867.
- Llombart, N., Neto, A., Gerini, G., Bonnedal, M. & Peter De Maagt. (2008). Leaky Wave Enhanced Feed Arrays for the Improvement of the Edge of Coverage Gain in Multibeam Reflector Antennas. *IEEE Trans. on Antennas and Propag.*, Vol. 56, No. 5, May, p.p. 1280-1291.
- Love, A. (1962). Spherical Reflecting Antennas with Corrected Line Sources. *IRE Trans. on Antennas and Propagation*, Vol. AP-10, September, No. 5-6, p.p.529-537.
- Miller, M. & Talanov, V. (1956). Electromagnetic Surface Waves Guided by a Boundary with Small Curvature. *Zh. Tekh. Fiz.*, Vol. 26, No. 12, p.p. 2755-2765.
- Ponomarev, O. (2008). Diffraction of Electromagnetic Waves by Concave Circumferential Surfaces: Application for Hybrid Reflector Antennas. *Bull. of the Russian Academy of Sciences: Physics*, Vol. 72, No. 12, p.p. 1666-1670.
- Rayleigh, J.W.S. (1945). *The Theory of Sound*, 2-nd ed., Vol. 2, Sec. 287, Dover Publication, ISBN 0-486-60293-1, New York.
- Schell, A. (1963). The Diffraction Theory of Large-Aperture Spherical Reflector Antennas. *IRE Trans. on Antennas and Propagation*, July, p.p. 428-432.
- Shevchenko, V. (1971). Radiation losses in bent waveguides for surface waves. *Institute of Radioengineering and Electronics, Academy of Sciences of the USSR. Translated from Izvestiya Vysshikh Uchebnykh Zavedenii, Radiofizika*, Vol. 14, No. 5, p.p. 768-777, May.
- Spencer, R., Sletten, C. & Walsh, J. (1949). Correction of Spherical Aberration by a Phased Line Source. *Proc. N.E.C.*, Vol. 5, p.p. 320-333.
- Tap, K. & Pathak, P.H. (2006). A Fast Hybrid Asymptotic and Numerical Physical Optics Analysis of Very Large Scanning Cylindrical Reflectors With Stacked Linear Array Feeds. *IEEE Trans. on Antennas and Propag.*, Vol. 54, No. 4, April, p.p. 1142-1151.
- Tingye, L. (1959). A Study of Spherical Reflectors as Wide-Angle Scanning Antennas. *IRE Trans. on Antennas and Propagation*, July, p.p. 223-226.

Badanie nowej metody korekcji aberacji sferycznej dla wzmocnionych sferycznych anten hybrydowych